


RTD Transmitter

MODEL SBPT

■ Features

- Simple wiring using a plug-in socket
- Compact
- 3-port insulation (Input-Output-Power)

■ Mode



M: 100 to 240V AC

R: 24V DC

■ How to order


Specify a model and input range. (e.g.) SBPT-4A-M 0 to 400°C

■ Input specifications

Input detection current: Approx. 0.2mA Allowable lead wire resistance: 10Ω or less per wire Burnout: Upscale, Downscale (Selectable by the DIP switch) Input:

RTD	Input range		
Pt100	-200 to 850°C	-328 to $1562^{\circ}F$	
JPt100	-200 to 500°C	-328 to 932°F	
Pt1000	-200 to 850°C	-328 to 1562 $^{\circ}\mathrm{F}$	
CU50	-50 to 150°C	-58 to 302°F	
CU100	-50 to 150°C	-58 to 302°F	

Minimum span: 50°C (100°F)



■ Output specifications

When the output range lower limit is zero, (even if zero adjustment results in a negative value), the output value will not be negative.

DC current

Output range	Allowable	Zero	Span
	load	adjustment	adjustment
	resistance	range	range
4 to 20mA DC	600Ω or less	-2.5 to 2.5%	97.5 to 102.5%
0 to 20mA DC	600Ω or less	0 to 2.5%	97.5 to 102.5%
0 to 12mA DC	1kΩ or less	0 to 2.5%	97.5 to 102.5%
0 to 10mA DC	1kΩ or less	0 to 2.5%	97.5 to 102.5%

DC voltage

Output range	Allowable	Zero	Span
	load	adjustment	adjustment
range	resistance	range	range
0 to 1V DC	100Ω or more	0 to 2.5%	97.5 to 102.5%
0 to 5V DC	500Ω or more	0 to 2.5%	97.5 to 102.5%
1 to 5V DC	500Ω or more	-2.5 to 2.5%	97.5 to 102.5%
0 to 10V DC	1kΩ or more	0 to 2.5%	97.5 to 102.5%

■ Performance

Accuracy : Within ±0.2% Response time : 1 sec. (0 \rightarrow 90%) (Average 0.5sec)

Temperature coefficient: ±0.015%/°C

: $10M\Omega$ or more, at 500V DC Insulation resistance

(Input-Output-Power) : 2.0kV AC for 1 minute

Dielectric strength (Input-Output-Power)

SB series

■ Instrument specifications

Case : Flame resistant resin Color: Light gray

Front panel : Polycarbonate

Spring type plug: Polyamide Color: Green Adjustment: By the front potentiometer

Zero adjustment : $\pm 2.5\%$ Span adjustment : $\pm 2.5\%$

Indication:

Power indicator (PWR): Green Lights when the power is turned on.

Flashes in 500ms cycles when an error has occurred

in non-volatile IC memory. Error indicator (ERR): Red

Flashes in 250ms cycles when input is 110% or more. Flashes in 500ms cycles when input is -10% or less.

Output status selection: Selects Normal or Reverse with

the DIP switch.

No.1 OFF: Normal, ON: Reverse

Burnout: Selects Upscale or Downscale with the DIP


switch.


No.2 OFF: Upscale, ON: Downscale Momentary power failure: 30msec.

Self diagnosis:

The CPU is monitored by a watchdog timer, and when an abnormal status is found on the CPU, the unit

restarts with the reset action.





■ Installation specifications

Power supply

• 100 to 240V AC 50/60Hz

Allowable voltage range: 85 to 264V AC Power consumption : Approx. 3.5VA

• 24V DC

Allowable voltage range: 20 to 28V DC Power consumption : Approx. 3.5W

Ambient temperature: -5 to 55°C

Ambient humidity : 35 to 85%RH (non-condensing)

Weight : Approx. 80g
Mounting method : DIN rail mounting

Be sure to use fastening plates at both ends of the unit after the unit

is mounted to the DIN rail.

External dimensions: 17.5 (W) x 75 (H) x 85 (D) mm

■ Environmental specification

RoHS directive compliance

■ Ferrules


Made by Phoenix Contact GMBH & CO.

Insulation sleeve attached

Model Conductor cross section AI0.25-6BU $0.2 - 0.25 \text{mm}^2$ $0.25 - 0.34 \text{mm}^2$ AI0.34-8TQ AI0.5-8WH $0.34 - 0.5 \text{mm}^2$ AI0.75-8GY $0.5 - 0.75 \text{mm}^2$ AI1-8RD $0.75 - 1.0 \text{mm}^2$ AI1.5-8BK $1.0 - 1.5 \text{mm}^2$ AI2.5-8BU $1.5 - 2.5 \text{mm}^2$

Crimping pliers CRIMPFOX ZA3 CRIMPFOX UD6

■ Circuit configuration, terminal arrangement



■ External dimensions (Scale: mm)

